

Home & Office Communication Centre



Base Station

Plain Paper

On conventional fax machines, the thermal paper soon curls and yellows. Not so with the FO-CC500, which uses plain paper for higher-quality, longer-life copies.

Digital Answering System

Say goodbye to low-fidelity analogue messages. The FO-CC500 saves your incoming messages in clearly-audible digital form.

448KB Memory

The FO-CC500's 448KB memory is big enough to save all those important incoming documents and messages. If you use the memory for documents only, you can save approximately 24 pages.*1 If you use the memory for voice messages only, you can save around 20 minutes of messages.

6-Second Transmission

When you're in a hurry, the FO-CC500 is here to help. Its speedy transmission time of 6 seconds means you're soon free to move on to the next job.

Caller ID*2

As with the cordless handset, the base station features Caller ID - especially handy for screening and keeping track of your calls.

- 40-Number Automatic Dialler
- 10-Sheet ADF*3
- 50-Sheet Paper Capacity
- 4-Point Operation Key



Cordless Handset

2.4GHz Frequency

The FO-CC500's handsets operate on an expandable 2.4GHz digital spread spectrum, so you can enjoy clearer sound and operate at longer distances from the base station.

Caller ID*2

For your convenience, the cordless handset features Caller ID, which clearly displays the name and number of the person calling.

Slim and Ergonomic Design

Sleek and slender, the cordless handset is shaped to please the eye as well as the ear. And its 3-line LCD display offers easy-to-read convenience.

- 15-Digit x 3-Line LCD Display
- Remote Fax Reception
- Remote Notification of New Messages

Three Optional Handsets Create More Possibilities



Personal Handsets

The FO-CC500's cordless handset gives you the freedom to roam. And now, on top of the one standard cordless handset and one attached handset, you get the option of three additional cordless handsets - one for everyone in the office.

Walkie Talkies

No matter how far you are from the base station, you can use the handsets as walkie talkies. Enjoy instant communication with other handset users

Remote Message Retrieval

No need to stand by the base unit while you check your messages. Wherever you are, you can use your handset to access your personal voice messages. Perfect for those concerned about privacy.

2-Way Intercom

Two users can communicate privately between handsets while a third user makes an outgoing call.

4 Voice Mail Boxes

Up to four users can have separate, privately accessible voice message boxes.

Specifications

Base Station Public switched telephone network Applicable line Data compression MH/MR/MMR Transmission time Approx. 6 sec.*4 14,400 to 2,400 bps with automatic fallback Modem speed Resolution Horizontal: 8 pels/mm (203 pels/inch) Vertical: 15.4 lines/mm (392 lines/inch) [Superfine] 7.7 lines/mm (196 lines/inch) [Fine/Halftone] 3.85 lines/mm (98 lines/inch) [Standard] Max. document width 216 mm (8.50") Max. scanning width 210 mm (8.27")

Max. recording width 210 mm (8.27") Copy function Single/Multi (99 copies/page) Power requirements Rated local AC voltage and frequency Max. 110 W, Standby: 3.5 W Power consumption

Dimensions (W x D x H) 353 x 193 x 174 mm (13.89" x 7.59" x 6.85")

Approx. 2.8 kg (6.2 lbs.) Weight

2.4 GHz Frequency Battery 3.6 V Ni-MH battery, Capacity: 850mAh Battery life Approx. 4 hours*5 (at room temperature) Battery life in standby mode Approx. 2 days*5 with one full charge (at room temperature) Power consumption

Approx. 1.6 W in standby mode (after charging) Dimensions (W x D x H) 46 x 42 x 180 mm (1.81" x 1.65" x 7.08") Weight Approx. 115 g (0.3 lbs.) without battery

Supplies

FO-6CR: 50m roll imaging film (one roll in one package)

UX-BA01 : Ni-MH battery

Cordless Handset

Design and specifications are current as of August 2003, but are subject to change without prior notice. *1 Based on Sharp's standard chart at standard resolution.

- *2 Caller ID may not be available in some regions. *3 80 g/m² A4 copier paper at room temperature.
- *4 Based on Sharp's standard chart at standard resolution (only when ECM is on).
- *5 Battery life (in both normal and standby modes) may vary depending on usage, range from base machine, and environmental conditions such as temperature



Distributed by: